

## MT8071iP V2.0






## New iP Series

- Wide input voltage range: 10.5~28VDC
- Boasts excellent performance with better operation experience compared to its predecessor.
- Weintek's compact HMI Series-iP has upgraded in every aspect to satisfy a variety of applications.
  - Equipped with Cortex A8 600MHz CPU.
  - Seamlessly upgraded from EB8000 to EasyBuilder Pro.


		Display	7" TFT LCD
		Resolution	800 x 480
	Display	Brightness (cd/m <sup>2</sup> )	300
		Contrast Ratio	500:1
		Backlight Type	LED
		Backlight Life Time	>30,000 hrs.
		Colors	16.7M
		LCD Viewing Angle (T/B/L/R)	70/50/70/70
		Pixel Pitch (mm)	0.1926(H) x 0.179(V)
	Touch Panel	Туре	4-wire Resistive Type
		Accuracy	Active Area Length(X)±2%, Width(Y)±2%
	Memory	Flash	128 MB
		RAM	128 MB
	Processor		32-bit RISC 600MHz
		USB Host	USB 2.0 x 1
	I/O Port	USB Client	N/A
		Ethernet	10/100 Base-T x 1
		COM Port	COM1: RS-232, COM2: RS-485 2W/4W
		RS-485 Dual Isolation	N/A
	RTC		Built-in
		Input Power	10.5~28VDC
		Power Consumption	1A@12VDC;500mA@24VDC
	Power	Power Isolation	Built-in
		Voltage Resistance	500VAC (1 min.)
		Isolation Resistance	Exceed 50MΩ at 500VDC
		Vibration Endurance	10 to 25Hz (X, Y, Z direction 2G 30 minutes)
	Specification	PCB Coating	N/A
		Enclosure	Plastic
		Dimensions WxHxD	200.4 x 146.5 x 34 mm
		Panel Cutout	192 x 138 mm
		Weight	Approx.0.52 kg
		Mount	Panel mount
	Environment	Protection Structure	NEMA4 / IP65 Compliant Front Panel
		Storage Temperature	-20°~60°C (-4° ~ 140°F)
		Operating Temperature	0° ~ 50°C (32° ~ 122°F)
		Relative Humidity	10% ~ 90% (non-condensing)
	Certificate	CE	CE marked
	Software		EasyBuilder Pro
			EasyAccess 2.0 (Optional)




## Dimensions




Front View




Side View



**Cutout Dimensions** 



Rear View



Pin Assignement:

COM1 [RS232] / COM2 [RS485] 9 Pin, Male, D-sub

PIN#	COM4 [DC222]	COM2 [RS485]	
PIN#	COM1 [RS232]	4W	2W
1		Rx-	Data-
2		Rx+	Data+
3		Tx-	
4		Tx+	
5	GND		
6	TxD		
7	RTS		
8	CTS		
9	RxD		

а	Power Connector	С	USB Host
h	COM1 RS232,	d	Ethernet
D	COM2 RS485 2W/4W	u	